

[Back](#)

www.dunlite.com.au

Phone: 1300 555 253 for your nearest dealer

DGUH2S-2

2.5 kVA - 2000 Watt, Honda powered generator

Power Rating: 2.5 kVA
 Cont. Output Watts: 1900 W
 Engine Model: Honda GX160
 Phase: 1-Phase
 Starting System: Recoil
 Fuel Tank Capacity: 1.5 L
 Noise Level @ 7m: 66 dBA
 Outlets: 2 x 10 Amp
 Operation Hours @ 80% Load: 3.3hr
 Fuel Type: Petrol
 Dimensions LxWxH: 650 x 460 x 415 mm
 Weight: 31 kg

ACCESSORIES

DGX01 - Wheel Barrow Kit
 Contains two handles and two leveling feet (requires the DGX05 Wheel Kit).

DGX02 - Remote Start Kit
 Suits models with electric start only.

DGX05 - Wheel Kit
 Contains two wheels.

DGX06 - One Axle & Two Wheels
 Suits models 9.5 kVA and above.

DGX08 - Earth Leakage Protection
 Contains two weather proof outlets (no earth stake). Available in 15 Amps, 20 Amps and 30 Amps.

DGX11 - 25 Litre Long Range Fuel Tank
 Suit 4.4 kVA models and above (does not suit Welders and Diesels).

DGX14 - Welder Leads
 8 metre long with clamp and holder.

LIFTING BAR KIT
 Suits models up to 3 kVA.

LIFTING BAR KIT 2
 Suits models ranging from 4.4 kVA to 8 kVA.



Specifications and product availability subject to variation without notice.



electric motors, generators, trailing cables & pumps - sales, service & repairs

571 Grand Junction Road Gepps Cross, SA 5094

(08) 8162 5957
 including after hours emergencies

Fax: (08) 8162 5058
info@aemgroup.net.au
www.aemgroup.net.au