

## TRACTOR PACS

Tractor pacs are power-take-off driven alternators that couple to most brands of tractors. They are fitted with a splined shaft for an input speed of approximately 400 rpm.

Ranging from 22 kVA to 100 kVA, all W&C Tractor Pacs are especially designed to run from the back of a tractor to back-up Dairies during down times, making them perfect for rural power applications. Convenient and sturdy, Tractor Pacs are a necessity for farmers wanting to protect their investment and peace-of-mind. Now with the option of the 22kVA and 31kVA in a 3 point carry frame for easy transpotation and manoeuvring around the farm.



Models Available	3 Phase (415 V)	2 Phase (480 V)	1 Phase (240 V)
Tractor Pac 20	22 kVA	15 kVA	15 kVA
Tractor Pac 20 in Frame	22kVA	15kVA	15kVA
Tractor Pac 30	31kVA	20kVA	20kVA
Tractor Pac 30 in Frame	31kVA	20kVA	20kVA
Tractor Pac 50	50kVA	30kVA	30kVA
Tractor Pac 50 in Frame	50kVA	30kVA	30kVA
Tractor Pac 60	60kVA	40 kVA	40 kVA
Tractor Pac 60 in Frame	60kVA	40 kVA	40kVA
Tractor Pac 85	85 kVA	50 kVA	50 kVA
Tractor Pac 100	100 kVA	67 kVA	67 kVA

**FREQUENCY** 50Hz

**ALTERNATOR SPEED** 4 pole, 1500 rpm

**GEARBOX** Fitted with splined shaft for an input speed of approximately 500 rpm.

**DIMENSIONS** 1100mm (L) x 450mm (W) x 500mm (H)

**DIMENSIONS IN FRAME** 1050MM (L) x 850mm (W) x 1030mm (H)

### OPTION AVAILABLE

**Digital Output Module** - Displays Amps, Volts, Frequency. Supplied loose for installation at site.